



Kvaser Memorator Light HS

EAN: 73-30130-00513-6

Designed for troubleshooting any CAN-based (controller area network) system, the Kvaser Memorator Light HS is an easy-to-use tool for logging serial data, with no preconfiguration or software setup required. With an autobaud function that determines CAN bus bit rate, the Kvaser Memorator Light can be attached to any high-speed CAN bus without configuration. All CAN bus traffic is logged in a circular buffer, overwriting the oldest data when the buffer becomes full. A separate circular buffer keeps track of error frame conditions and the message traffic that occurs near the conditions.

Major Features

- Single high-speed CAN channel (compliant with ISO 11898-2).
- Supports both 11-bit (CAN 2.0A) and 29-bit (CAN 2.0B active) identifiers.
- Supports bit rates from 10 Kbit/sec up to 1 Mbit/sec.
- Auto detects bit rate - removes the need for configuration.
- Always in silent mode - log bus traffic without interfering.

- 1 GByte of internal memory for message storage.
- All received CAN frames recorded in a circular buffer - oldest data overwritten by newest.
- A second circular buffer records 1000 messages before and after an error frame occurs.
- The Kvaser Memorator Light extraction software provides easy access to the recorded data when connected to the device via a USB port. The tool supports multiple formats used by popular analysis software. In addition, the extraction software allows the user to clear and reinitialize the device's memory

Warranty

- 2-Year Warranty. See our General Conditions and Policies for details.

Support

- Free Technical Support on all products available by contacting support@kvaser.com

Software

- Documentation, software and drivers can be downloaded for free at www.kvaser.com/downloads.
- Kvaser CANLIB SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, and Visual Basic.
- All Kvaser CAN interface boards share a common software API. Programs written for one interface type will run without modifications on the other interface types!
- J2534 Application Programming Interface available.
- RP1210A Application Programming Interface available.
- On-line documentation in Windows HTML-Help and Adobe Acrobat format.

TECHNICAL DATA - KVASER MEMORATOR LIGHT HS

API, FREE	Kvaser API, J2534, RP 1210
RUGGED	No
OPERATING SYSTEM	Win Vista,Win 8,Win 7,Win XP
IP CLASS	N/A
CERTIFICATIONS	CE,RoHS
MSGRATE RX MAX	20000
WIDTH (MM)	50
CONNECTOR	DSUB 9
CASING MATERIAL	-
ERROR FRAME DETECTION	Yes
STATUS	Active
API, LICENCED	None
TIMESTAMP RESOLUTION (US)	2
SILENT MODE	Yes
ON-BOARD BUFFER	Yes
PC INTERFACE	USB
ON-BOARD RX BUFFER	N/A
ERROR COUNTERS READING	No
HEIGHT (MM)	25
MSGRATE TX MAX	N/A
LENGTH (MM)	90
GALVANIC ISOLATION	No
EMBEDDED SCRIPT	No
# OF CAN CHANNELS	1
SOUND	No
ERROR FRAME GENERATION	No



Kvaser Memorator Light HS

MINIMUM BITRATE (KBPS)	10
MAXIMUM BITRATE (KBPS)	1000
CLOCK SYNC	No
WEIGHT (G)	150.0
NETWORK CHANNEL(S)	1 x CAN HS
ON-BOARD TX BUFFER	N/A
OPERATING TEMPERATURE RANGE (C)	-40.00 to 85.00

The information herein is subject to change without notice